

Home Assistant

Everything to do with Home Assistant

- [Dual Garage Door Opener](#)

Dual Garage Door Opener

Using ESPHome

This is code for dual garage door opener and will show red when door is opened

Dashboard

 image.png
Image not found or type unknown

This is built using a

ESP32

and some magnet switches

REED

The REED is only one per door

substitutions:

name: sfl-garage-001

friendly_name: SFL-GARAGE-001

esphome:

name: \${name}

name_add_mac_suffix: false

friendly_name: \${friendly_name}

esp32:

board: esp32dev

framework:

type: esp-idf

wifi:

ssid: !secret wifi_ssid

password: !secret wifi_password

ap:

ssid: "Sfl-Garage-001 Fallback Hotspot"

password: "xxx"

api:

encryption:

key: "xxxxxx"

ota:

- platform: esphome

password: "xxxxx"

logger:

level: ERROR

web_server:

port: 80

bluetooth_proxy:

active: true

captive_portal:

--- Relays (momentary button press) ---

switch:

- platform: gpio

pin: GPIO25

inverted: true

name: "Door 1 Button"

id: garage_button_1

on_turn_on:

- delay: 500ms

- switch.turn_off: garage_button_1

- platform: gpio

pin: GPIO32

inverted: true

name: "Door 2 Button"

id: garage_button_2

on_turn_on:

- delay: 500ms

- switch.turn_off: garage_button_2

--- Reed Switches ---

binary_sensor:

- platform: gpio

pin:

number: GPIO05

mode: INPUT_PULLUP

inverted: false

name: "Door 1 Sensor"

id: garage_sensor_1

device_class: garage_door

icon: "mdi:garage"

filters:

- delayed_on: 100ms

- delayed_off: 100ms

- platform: gpio

pin:

number: GPIO04

mode: INPUT_PULLUP

inverted: false

name: "Door 2 Sensor"

id: garage_sensor_2

device_class: garage_door

icon: "mdi:garage"

filters:

- delayed_on: 100ms

- delayed_off: 100ms

--- Garage Door Covers ---

cover:

- platform: template

name: "Door 1"

device_class: garage

optimistic: false

lambda: |-

if (id(garage_sensor_1).state) {

return COVER_CLOSED;

} else {

return COVER_OPEN;

}

open_action:

- switch.turn_on: garage_button_1

close_action:

- switch.turn_on: garage_button_1

stop_action:

- switch.turn_on: garage_button_1

- platform: template

name: "Door 2"

device_class: garage

optimistic: false

lambda: |-

```
if (id(garage_sensor_2).state) {  
    return COVER_CLOSED;  
} else {  
    return COVER_OPEN;  
}
```

open_action:

- switch.turn_on: garage_button_2

close_action:

- switch.turn_on: garage_button_2

stop_action:

- switch.turn_on: garage_button_2